arXiv:quant-ph/9809055v2 18 Sep 1998

An Optimization for Qubiter

Robert R. Tucci
P.O. Box 226
Bedford, MA 01730
tucci@ar-tiste.com

February 1, 2008

Abstract

In a previous paper, we described a computer program called Qubiter which can decompose an arbitrary unitary matrix into elementary operations of the type used in quantum computation. In this paper, we describe a method of reducing the number of elementary operations in such decompositions.

According to Eqs.(4.17) and (4.18) of Ref.[1], if we define $\Gamma(\theta)$ by

$$\Gamma(\theta) = \exp(i\theta\sigma_y) \otimes I_2 \otimes I_2 \ , \tag{1}$$

then

$$D = \prod_{\vec{b} \in Bool^2} A_{\vec{b}} \ , \tag{2}$$

where

$$A_{00} = \Gamma(\theta_{00}) \ , \tag{3a}$$

$$A_{10} = \sigma_x(2)^{n(1)} \odot \Gamma(\theta_{10}) \ , \tag{3b}$$

$$A_{11} = [\sigma_x(2)^{n(1)} \sigma_x(2)^{n(0)}] \odot \Gamma(\theta_{11}) \ , \tag{3c}$$

$$A_{01} = \sigma_x(2)^{n(0)} \odot \Gamma(\theta_{01}) \ . \tag{3d}$$

The operators $A_{\vec{b}}$ commute so Eq.(2) is valid regardless of the order in which the $A_{\vec{b}}$ are multiplied. Suppose we multiply them in the following order:

$$D = A_{01} A_{11} A_{10} A_{00} \ . \tag{4}$$

Note that in this order, if $A_{\vec{b}_L}$ is immediately to the left of $A_{\vec{b}_R}$, then $\vec{b}_L$ and $\vec{b}_R$ are elements of $Bool^2$ that differ only in the value of one bit. Eq.(4) simplifies to

$$D = \sigma_x(2)^{n(0)} \Gamma(\theta_{01}) \sigma_x(2)^{n(1)} \Gamma(\theta_{11}) \sigma_x(2)^{n(0)} \Gamma(\theta_{10}) \sigma_x(2)^{n(1)} \Gamma(\theta_{00}) \ . \tag{5}$$

We see that by ordering the $A_{\vec{b}}$ in this special way, many c-nots cancel out. Only one c-not remains between any two adjacent Γ's. There is no c-not to the right of the rightmost Γ in Eq.(5). And, because the leftmost $\vec{b}$ in Eq.(4) has only one non-zero bit, there is only one c-not to the left of the leftmost Γ in Eq.(5).

The above example assumes $N_B = 3$ and that we are decomposing a central matrix of type 1 (i.e., a central matrix which is a single D matrix). However, this method of reducing the number of c-nots in a decomposition can also be used for other values of N_B and for the other two types of central matrices. Let's see how. For general N_B, one can (see Appendix) order the elements $\vec{b}$ of $Bool^{N_B}$ so that adjacent $\vec{b}$'s differ only in the value of one bit, and so that the first $\vec{b}$ is the zero vector and the last $\vec{b}$ is a standard unit vector (i.e., it has only one non-zero bit). We'll call such an ordering of the elements of $Bool^{N_B}$ a "lazy" ordering (a step from one $\vec{b}$ to the next is "lazy" since it involves a single bit flip instead of many). Products of $A_{\vec{b}}$ operators arise in the decomposition of all three types of central matrices. If the

order in which one multiples the $A_{\vec{b}}$ is such that their $\vec{b}$ subscripts are in a lazy order, then the number of c-nots in the decomposition will be reduced.

APPENDIX: A Method of Generating a Lazy Ordering of $Bool^{N_B}$

Create a binary tree T with $N_B - 1$ levels. Label each node of T by its level number (top is 0, bottom is $N_B - 1$). See Fig.1 for T when $N_B = 3$. Create a sequence $s = (s_1, s_2, \cdots, s_{N_S - 1})$ of integers by recording the node labels encountered during an "inorder transversal" of the tree. For example, for Fig.1, $s = (2, 1, 2, 0, 2, 1, 2)$. Let $\vec{b}_0 = \vec{0} \in Bool^{N_B}$. On step $j \in \{1, 2, \ldots, N_S - 1\}$, $\vec{b}_{j-1}$ transforms into $\vec{b}_j$ when you flip the bit at position s_j. As usual, we label the bit positions so that they increase from right to left and the rightmost bit is at position 0.



Fig.1 A lazy ordering of $Bool^3$

References

[1] R. R. Tucci, "A Rudimentary Quantum Compiler", Los Alamos eprint quant-ph/9805015